



## **WE-JMP 412B**

### **Portable 4 Bands x 3Watt Adjustable Jammer**

The WE-JMPR 412B can be applied at meeting room, conference room, museum, gallery, theatre, concert hall, church, temple, restaurant, classroom, training center, factory, bank, train, bus, etc.

easy to install and operate the device. No adjustment is needed.

The WE-JMP 412B is installed in waterproof Pelican Case and can adjust the power output of every channel (Hi-Low) with dipswitches .

Include 4 external Dipoles omni direction antennas and 12V DC adaptor / charger

#### **Specifications**

\* **Tx Frequency**

851-894 MHz

925/935-960 MHz

1805-1990 MHz

2100-2170 MHz

\* **Cover interface standards**

Digital: IDEN TDMA, CDMA, GSM, UMTS,CDMA1900,3G

Analog: AMPS, NMT, N-AMPS, TACS

**Every band frequency can select output power Hi & Low by Dip SW**

\* **Total output power**

Low Total 6W: 800MHz:1.5W, 900MHz:1.5W,1800-1900MHz:1.5W, 2100MHz 1.5W

Hi Total 12W : 800MHz:3W, 900MHz:3W, 1800-1900MHz:3W, 2100MHz:3W

\* **Signal Source**

PLL synthesized

\* **Continue using time**

90 minutes with battery and continuously when plugged to 110V-220Volt Power

\* **All the TX frequency covered down link only**

\* **Automatic power switching power supply**

50 / 60 Hz / AC 100 ~ 240V transmitting to DC 12V

\* **Working temperature**

-10C to +60C With thermostat 2 auto cooling fan

\* **Jamming range**

Radius 20~50 M 【 the signal must < -80dBm in the location 】 The jamming radius still depends on the strength signal in given area

\* **Safety regulation**

AC Adapter UL ( E190582 ), CSA ( LR112971 Level 3 )

Carcom 5 Modeen Israel

Tel: +972-57-6550444 Fax: +972-57-1534954389 Mobile: +972-57-4954389

Site: [www.wiseeye.co.il](http://www.wiseeye.co.il) mail: [office@wiseeye.co.il](mailto:office@wiseeye.co.il)